

VDV-800-V-HPH

Design : Vanderveen
 Manufacturing : Trafco D.O.O.
 Date : 2018-01-22
 Description : Headphone OPT ; 1 W ; 800 to 16 → 600 Ω
 Primary : $Z_p = 800 \Omega$ / $R_{ip} = 18 \Omega$ / $L_p = 40 \text{ H}$ / $f_{-3L} = 3 \text{ Hz}$
 : lead-outs RED-BLK at 12.00
 Secondary : $Z_s = 600\text{-(BLU)} / 300 / 125 / 64 / 32 / 16 / 0\text{-(BLK)} \Omega$
 Remarks : RED-primary and BLUE-secondary are in phase
 : Primary and Secondary are isolated for: $V(\text{prim to sec}) < 500 \text{ Vrms}$

Lead-out clock position	Z_s [Ω]	R_{is} [Ω]	L_{sp} [mH]	f-3H $R_{source} = 100 \Omega$	Q $R_{source} = 100 \Omega$	f-3H $R_{source} = 400 \Omega$	Q $R_{source} = 400 \Omega$
4.30-BLU	600	19	0,04	3,6 M	0,55	3,1 M	0,613
5.00-WHT	300	9,5	0,08	2 M	0,48	2 M	0,69
5.30-WHT	125	7	0,2	784 k	0,34	1,2 M	0,655
6.00-WHT	64	5	0,7	362 k	0,25	612 k	0,54
6.30-WHT	32	4	1,2	161 k	0,17	270 k	0,4
7.00-WHT	16	3	1,5	71 k	0,11	116 k	0,3
7.30-BLK	0	[Ω]	[mH]	[Hz]	[]	[Hz]	[]

f-3H = highest -3dB frequency ; Q = quality factor of high frequency 2-nd order low pass transfer

